

CONVERTS 0-1mA INPUT TO VOLTAGE OUTPUT

DESCRIPTION

The LRB series converters provide a precision resistor in a ruggedized enclosure. Standard resistor values from 500Ω to 10000Ω are available. Non-standard values from 200Ω to 10000Ω are also available. Consult factory for non-standard models.



**5 YEAR
WARRANTY**

MODEL SELECTION

DC OUTPUT REQUIRED	LOAD RESISTANCE (Ω)	MODEL
0-500mV	500	LRB-500
0-1V	1000	LRB-1000
0-2V	2000	LRB-2000
0-5V	5000	LRB-5000
0-10V	10000	LRB-10000

Non-standard resistance values available for 200 - 10000Ω .
Substitute desired load resistance in model number LRB-xxxx

ORDERING INFORMATION

Example: 0-1mA Input, 0-2V Output

LRB-2000

SPECIFICATIONS**INPUT**

Current 0-1mAdc

OUTPUT


Voltage See Table
Load Resistance See Table

ACCURACY

500 - 10000Ω models $\pm 0.1\%$
 200 - 499Ω models $\pm 0.2\%$

TEMPERATURE

Operating Range - 20°C to + 70°C
Effect $\pm 0.005\%/\text{ }^\circ\text{C}$

CASE DIMENSIONS

All dimensions in inches

Dwg# 0902-00891-B

OHIO SEMITRONICS, INC.

4242 REYNOLDS DRIVE * HILLIARD, OHIO * 43026-1264
PHONE: (614) 777-1005 * FAX: (614) 777-4511
WWW.OHIOSEMITRONICS.COM * 1-800-537-6732