## OPEN CIRCUIT PROTECTION FOR CURRENT TRANSFORMERS

### **DESCRIPTION**

The OCP-35 design provides protection from the dangerously high voltages (≥100V) that can be generated by open circuit current transformer secondaries. If secondary voltage rises above approximately 35Vpk the OCP-35 quickly clamps it to a non-destructive level of less than 1.5V. Clamping continues until the next zero crossing at which time it resets or clamps again if high voltage is still present. Both positive and negative half-cycles of a sinewave are clamped. In normal operation the OCP-35 creates negligible leakage current and does not introduce phase or ratio errors.



## **SPECIFICATIONS**

Current	Range	0-5A	
	•	Continuous10A	
Frequency	Range	20-500Hz	
Leakage CurrentTypical @ 25°C0.05mA			

#### **PROTECTION**

**INPUT** 

Breakover Voltage	Typical	35Vpk
	Range	33-43Vpk
Clamping Voltage	Typical	1V
	Maximum	1.5V
Response		25us

#### **TEMPERATURE**

Operating Rand	je	-40°C	to 65	5°C


#### PHYSICAL


Lead Length	
OCP-35	4.5 in. Typical, 16AWG
*OCP-35-9	9.0 in. Typical 16AWG
Termination	#10 Ring Terminals
Weight Typical	1 oz

NOTE: CONNECTIONS ARE NOT POLARIZED.

# **DIMENSIONS AND CONNECTIONS**

DIMENSIONS IN INCHES, TOLERANCE IS ±0.0625 IN.





Dwg# 0902-01089-A Rev--

OHIO SEMITRONICS, INC. 4242 REYNOLDS DRIVE\*HILLIARD, OHIO\*43026-1264 PHONE: (614) 777-1005 \* FAX: (614) 777-4511 www.ohiosemitronics.com \* 1-800-537-6732